



PowerSafe[®]

SBS Performance Specifications

Constant Current Discharge Performance Data

Discharge Currents (Amperes) to 1.75Vpc at 77°F (25°C)

| Battery Type | Standby Time (Minutes) | | | Standby Time (Hours) | | | | | | | | | |
|--------------|------------------------|-------|-------|----------------------|-------|-------|------|------|------|------|------|------|------|
| | 15 | 30 | 45 | 1 | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 10 | 20 |
| SBS 8 | 18.0 | 10.4 | 7.5 | 5.8 | 3.2 | 2.2 | 1.7 | 1.4 | 1.2 | 1.1 | 0.9 | 0.8 | 0.4 |
| SBS 15 | 32.8 | 19.5 | 14.1 | 11.2 | 6.2 | 4.4 | 3.4 | 2.8 | 2.4 | 2.0 | 1.8 | 1.5 | 0.8 |
| SBS 30 | 61.1 | 36.1 | 26.1 | 20.6 | 11.4 | 8.0 | 6.2 | 5.1 | 4.3 | 3.8 | 3.3 | 2.8 | 1.5 |
| SBS 40 | 83.4 | 50.7 | 37.0 | 29.3 | 16.3 | 11.4 | 8.9 | 7.3 | 6.2 | 5.4 | 4.7 | 3.9 | 2.1 |
| SBS 60 | 108.9 | 66.7 | 48.9 | 39.0 | 22.0 | 15.5 | 12.1 | 9.9 | 8.4 | 7.3 | 6.5 | 5.3 | 2.8 |
| SBS 110 | 209.2 | 135.1 | 101.4 | 81.9 | 47.6 | 34.0 | 26.7 | 22.0 | 18.8 | 16.4 | 14.6 | 12.0 | 6.5 |
| SBS 130 | 246.1 | 156.2 | 116.8 | 94.2 | 54.7 | 39.2 | 30.7 | 25.3 | 21.6 | 18.9 | 16.7 | 13.7 | 7.4 |
| SBS 300 | 602.7 | 384.5 | 283.7 | 227.3 | 129.3 | 90.7 | 71.0 | 58.6 | 50.0 | 43.7 | 39.0 | 32.2 | 17.7 |
| SBS 390 | 647.4 | 427.3 | 323.3 | 261.6 | 152.1 | 108.8 | 84.9 | 69.8 | 59.2 | 51.5 | 45.7 | 37.0 | 19.9 |
| SBS J13 | 27.5 | 16.5 | 11.9 | 9.4 | 5.2 | 3.7 | 2.9 | 2.3 | 2.0 | 1.7 | 1.5 | 1.2 | 0.6 |
| SBS J16 | 34.5 | 20.9 | 15.2 | 12.0 | 6.8 | 4.8 | 3.7 | 3.0 | 2.6 | 2.2 | 2.0 | 1.6 | 0.8 |
| SBS J30 | 63.3 | 37.9 | 27.3 | 21.5 | 11.8 | 8.2 | 6.3 | 5.2 | 4.4 | 3.8 | 3.4 | 2.7 | 1.5 |
| SBS J40 | 89.3 | 54.4 | 39.6 | 31.3 | 17.4 | 12.2 | 9.4 | 7.7 | 6.5 | 5.7 | 5.0 | 4.1 | 2.2 |
| SBS J70 | 151.1 | 91.6 | 66.3 | 52.2 | 28.6 | 19.8 | 15.2 | 12.4 | 10.4 | 9.0 | 7.9 | 6.4 | 3.4 |
| SBS B8(F) | 68.8 | 40.2 | 29.2 | 23.1 | 13.1 | 9.2 | 7.2 | 5.9 | 5.0 | 4.4 | 3.9 | 3.2 | 1.7 |
| SBS B10(F) | 79.8 | 47.6 | 34.5 | 27.2 | 15.3 | 10.9 | 8.5 | 7.1 | 6.1 | 5.4 | 4.8 | 4.0 | 2.2 |
| SBS B14(F) | 122.8 | 76.1 | 56.4 | 45.1 | 25.7 | 18.2 | 14.3 | 11.8 | 10.1 | 8.8 | 7.8 | 6.4 | 3.5 |
| SBS C11(F) | 172.6 | 109.3 | 80.9 | 64.7 | 37.0 | 26.3 | 20.5 | 17.0 | 14.5 | 12.8 | 11.4 | 9.5 | 5.3 |
| SBS 100(F) | 195.9 | 126.1 | 94.2 | 75.4 | 43.1 | 30.5 | 23.7 | 19.4 | 16.5 | 14.4 | 12.8 | 10.5 | 5.8 |
| SBS 112F | 196.3 | 128.4 | 97.2 | 78.9 | 46.1 | 33.0 | 25.8 | 21.3 | 18.1 | 15.8 | 14.0 | 11.4 | 5.9 |
| SBS 145(F) | 262.0 | 164.8 | 122.1 | 98.1 | 56.4 | 40.1 | 32.0 | 26.7 | 23.1 | 20.3 | 18.2 | 15.0 | 7.7 |
| SBS 165F | 303.0 | 195.0 | 146.0 | 120.0 | 68.5 | 48.5 | 37.8 | 31.0 | 26.9 | 23.5 | 20.8 | 17.0 | 9.5 |
| SBS 170F | 293.7 | 199.2 | 152.4 | 124.0 | 71.7 | 51.0 | 39.6 | 32.5 | 27.7 | 24.2 | 21.5 | 17.7 | 9.6 |
| SBS 190F | 332.7 | 222.8 | 169.3 | 137.4 | 79.9 | 57.1 | 44.5 | 36.6 | 31.1 | 27.2 | 24.1 | 19.8 | 10.7 |

Discharge Currents (Amperes) to 1.80Vpc at 77°F (25°C)

| Battery Type | Standby Time (Minutes) | | | Standby Time (Hours) | | | | | | | | | |
|--------------|------------------------|-------|-------|----------------------|-------|-------|------|------|------|------|------|------|------|
| | 15 | 30 | 45 | 1 | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 10 | 20 |
| SBS 8 | 17.5 | 10.2 | 7.3 | 5.7 | 3.2 | 2.2 | 1.7 | 1.4 | 1.2 | 1.0 | 0.9 | 0.8 | 0.4 |
| SBS 15 | 32.0 | 19.2 | 13.9 | 11.0 | 6.1 | 4.3 | 3.4 | 2.7 | 2.3 | 2.0 | 1.8 | 1.4 | 0.8 |
| SBS 30 | 59.4 | 35.5 | 25.7 | 20.3 | 11.2 | 7.9 | 6.1 | 5.0 | 4.3 | 3.7 | 3.3 | 2.7 | 1.5 |
| SBS 40 | 80.8 | 49.7 | 36.3 | 28.8 | 16.1 | 11.3 | 8.7 | 7.2 | 6.1 | 5.3 | 4.7 | 3.8 | 2.1 |
| SBS 60 | 104.8 | 65.2 | 48.0 | 38.3 | 21.7 | 15.3 | 11.9 | 9.8 | 8.3 | 7.2 | 6.4 | 5.2 | 2.8 |
| SBS 110 | 198.6 | 130.6 | 98.7 | 79.9 | 46.7 | 33.5 | 26.3 | 21.7 | 18.5 | 16.2 | 14.4 | 11.8 | 6.4 |
| SBS 130 | 234.0 | 150.7 | 113.4 | 91.6 | 53.6 | 38.5 | 30.2 | 25.0 | 21.3 | 18.6 | 16.5 | 13.5 | 7.3 |
| SBS 300 | 561.6 | 363.2 | 268.3 | 216.1 | 123.3 | 87.3 | 68.6 | 56.9 | 48.8 | 42.8 | 38.3 | 31.8 | 17.7 |
| SBS 390 | 615.6 | 412.9 | 314.3 | 255.0 | 149.1 | 106.9 | 83.6 | 68.7 | 58.4 | 50.8 | 45.1 | 36.6 | 19.7 |
| SBS J13 | 26.6 | 16.1 | 11.7 | 9.3 | 5.2 | 3.6 | 2.8 | 2.3 | 1.9 | 1.7 | 1.5 | 1.2 | 0.6 |
| SBS J16 | 33.2 | 20.3 | 14.8 | 11.8 | 6.6 | 4.7 | 3.6 | 3.0 | 2.5 | 2.2 | 1.9 | 1.6 | 0.8 |
| SBS J30 | 61.0 | 36.9 | 26.7 | 21.1 | 11.6 | 8.1 | 6.3 | 5.1 | 4.3 | 3.8 | 3.3 | 2.7 | 1.4 |
| SBS J40 | 85.4 | 52.7 | 38.6 | 30.7 | 17.1 | 12.0 | 9.3 | 7.6 | 6.4 | 5.6 | 4.9 | 4.0 | 2.1 |
| SBS J70 | 143.0 | 88.2 | 64.3 | 50.9 | 28.1 | 19.5 | 15.0 | 12.2 | 10.3 | 8.9 | 7.8 | 6.3 | 3.3 |
| SBS B8(F) | 67.7 | 39.5 | 28.5 | 22.6 | 12.9 | 9.1 | 7.1 | 5.9 | 5.0 | 4.3 | 3.8 | 3.1 | 1.7 |
| SBS B10(F) | 77.4 | 47.0 | 34.0 | 26.8 | 15.2 | 10.7 | 8.4 | 7.0 | 6.0 | 5.3 | 4.8 | 4.0 | 2.2 |
| SBS B14(F) | 115.4 | 72.7 | 54.3 | 43.7 | 25.1 | 18.0 | 14.1 | 11.7 | 10.0 | 8.8 | 7.8 | 6.4 | 3.4 |
| SBS C11(F) | 163.0 | 105.0 | 78.5 | 63.1 | 36.5 | 26.0 | 20.4 | 16.9 | 14.4 | 12.7 | 11.4 | 9.4 | 5.3 |
| SBS 100(F) | 181.4 | 118.9 | 89.9 | 72.5 | 41.9 | 29.9 | 23.2 | 19.1 | 16.2 | 14.1 | 12.6 | 10.4 | 5.7 |
| SBS 112F | 182.1 | 121.7 | 93.1 | 76.1 | 45.0 | 32.3 | 25.4 | 20.9 | 17.8 | 15.5 | 13.8 | 11.2 | 5.8 |
| SBS 145F | 244.9 | 158.2 | 118.3 | 95.5 | 55.1 | 39.4 | 31.4 | 26.2 | 22.6 | 19.9 | 17.8 | 14.6 | 7.5 |
| SBS 165F | 283.0 | 186.0 | 141.0 | 116.0 | 67.1 | 47.6 | 37.1 | 30.5 | 26.5 | 23.1 | 20.5 | 16.8 | 9.0 |
| SBS 170F | 266.2 | 187.8 | 145.7 | 119.4 | 69.9 | 49.9 | 38.9 | 32.0 | 27.2 | 23.8 | 21.2 | 17.4 | 9.4 |
| SBS 190F | 304.6 | 209.8 | 161.6 | 132.2 | 77.9 | 56.0 | 43.8 | 36.0 | 30.7 | 26.8 | 23.8 | 19.5 | 10.6 |

Constant Current Discharge Performance Data continued

Discharge Currents (Amperes) to 1.85Vpc at 77°F (25°C)

| Battery Type | Standby Time (Minutes) | | | Standby Time (Hours) | | | | | | | | | |
|--------------|------------------------|-------|-------|----------------------|-------|-------|------|------|------|------|------|------|------|
| | 15 | 30 | 45 | 1 | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 10 | 20 |
| SBS 8 | 16.8 | 9.9 | 7.2 | 5.6 | 3.1 | 2.1 | 1.7 | 1.4 | 1.2 | 1.0 | 0.9 | 0.7 | 0.4 |
| SBS 15 | 30.8 | 18.7 | 13.6 | 10.7 | 6.0 | 4.2 | 3.3 | 2.7 | 2.3 | 2.0 | 1.7 | 1.4 | 0.7 |
| SBS 30 | 57.1 | 34.5 | 25.0 | 19.8 | 10.9 | 7.7 | 5.9 | 4.9 | 4.1 | 3.6 | 3.2 | 2.6 | 1.4 |
| SBS 40 | 76.9 | 48.0 | 35.2 | 28.1 | 15.6 | 11.0 | 8.5 | 7.0 | 5.9 | 5.1 | 4.5 | 3.7 | 2.0 |
| SBS 60 | 98.6 | 62.4 | 46.3 | 36.9 | 21.1 | 14.9 | 11.6 | 9.5 | 8.1 | 7.0 | 6.2 | 5.1 | 2.7 |
| SBS 110 | 186.4 | 125.1 | 94.7 | 76.9 | 45.4 | 32.5 | 25.5 | 21.2 | 18.1 | 15.8 | 14.0 | 11.5 | 6.3 |
| SBS 130 | 220.4 | 144.1 | 108.2 | 87.7 | 51.7 | 37.4 | 29.3 | 24.2 | 20.7 | 18.1 | 16.1 | 13.2 | 7.1 |
| SBS 300 | 512.7 | 325.2 | 243.1 | 196.3 | 113.6 | 81.5 | 64.7 | 53.9 | 46.4 | 40.9 | 36.8 | 30.8 | 17.6 |
| SBS 390 | 573.5 | 394.0 | 300.2 | 244.4 | 145.2 | 103.6 | 80.9 | 67.0 | 57.0 | 49.5 | 44.0 | 35.8 | 19.6 |
| SBS J13 | 25.2 | 15.5 | 11.4 | 9.0 | 5.0 | 3.5 | 2.7 | 2.2 | 1.9 | 1.6 | 1.5 | 1.2 | 0.6 |
| SBS J16 | 31.4 | 19.6 | 14.3 | 11.4 | 6.4 | 4.5 | 3.5 | 2.9 | 2.4 | 2.1 | 1.9 | 1.5 | 0.8 |
| SBS J30 | 57.6 | 35.6 | 25.9 | 20.4 | 11.3 | 7.9 | 6.1 | 5.0 | 4.2 | 3.6 | 3.2 | 2.6 | 1.4 |
| SBS J40 | 80.1 | 50.4 | 37.3 | 29.5 | 16.6 | 11.7 | 9.0 | 7.4 | 6.2 | 5.4 | 4.8 | 3.9 | 2.1 |
| SBS J70 | 133.3 | 83.5 | 61.4 | 48.9 | 27.3 | 19.0 | 14.6 | 11.9 | 10.0 | 8.6 | 7.6 | 6.2 | 3.2 |
| SBS B8(F) | 66.8 | 38.8 | 28.0 | 22.0 | 12.5 | 8.9 | 7.0 | 5.8 | 4.9 | 4.3 | 3.8 | 3.1 | 1.6 |
| SBS B10(F) | 73.7 | 45.9 | 33.1 | 26.1 | 14.7 | 10.4 | 8.2 | 6.8 | 5.8 | 5.2 | 4.7 | 3.9 | 2.2 |
| SBS B14(F) | 106.5 | 68.2 | 51.4 | 41.5 | 24.3 | 17.4 | 13.8 | 11.5 | 9.8 | 8.6 | 7.7 | 6.3 | 3.4 |
| SBS C11(F) | 151.8 | 99.4 | 74.8 | 60.5 | 35.5 | 25.7 | 20.3 | 16.7 | 14.3 | 12.6 | 11.2 | 9.3 | 5.2 |
| SBS 100(F) | 164.3 | 110.6 | 84.0 | 67.9 | 40.2 | 28.8 | 22.6 | 18.6 | 15.8 | 13.8 | 12.2 | 10.1 | 5.6 |
| SBS 112F | 164.6 | 113.0 | 87.4 | 71.6 | 43.2 | 31.2 | 24.5 | 20.2 | 17.2 | 15.0 | 13.3 | 10.8 | 5.6 |
| SBS 145F | 224.0 | 148.0 | 112.4 | 91.3 | 52.9 | 38.3 | 30.5 | 25.4 | 21.9 | 19.3 | 17.2 | 14.1 | 7.3 |
| SBS 165F | 261.0 | 176.0 | 135.0 | 112.0 | 65.3 | 46.6 | 36.4 | 29.9 | 26.0 | 22.7 | 20.1 | 16.5 | 8.0 |
| SBS 170F | 246.6 | 175.0 | 137.9 | 113.3 | 67.2 | 48.1 | 37.6 | 30.9 | 26.3 | 22.9 | 20.4 | 16.7 | 9.1 |
| SBS 190F | 275.2 | 194.2 | 151.8 | 124.7 | 74.9 | 54.3 | 42.4 | 35.0 | 29.9 | 26.1 | 23.2 | 19.0 | 10.3 |

Constant Power Discharge Performance Data

Discharge Power (Watts per Cell) to 1.75Vpc at 77°F (25°C)

| Battery Type | Standby Time (Minutes) | | | Standby Time (Hours) | | | | | | | | | |
|--------------|------------------------|-----|-----|----------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| | 15 | 30 | 45 | 1 | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 10 | 20 |
| SBS 8 | 34 | 20 | 14 | 11 | 6.2 | 4.3 | 3.4 | 2.8 | 2.3 | 2.0 | 1.8 | 1.5 | 0.8 |
| SBS 15 | 62 | 37 | 27 | 21 | 12 | 8.5 | 6.6 | 5.4 | 4.6 | 4.0 | 3.5 | 2.9 | 1.5 |
| SBS 30 | 116 | 69 | 50 | 40 | 22 | 15 | 12 | 10 | 8.4 | 7.3 | 6.5 | 5.3 | 2.9 |
| SBS 40 | 157 | 96 | 71 | 56 | 32 | 22 | 17 | 14 | 12 | 10 | 9.2 | 7.5 | 4.1 |
| SBS 60 | 203 | 126 | 93 | 74 | 42 | 30 | 23 | 19 | 16 | 14 | 13 | 10 | 5.5 |
| SBS 110 | 385 | 253 | 191 | 155 | 91 | 65 | 51 | 42 | 36 | 32 | 28 | 23 | 13 |
| SBS 130 | 456 | 293 | 221 | 179 | 105 | 75 | 59 | 49 | 42 | 36 | 32 | 27 | 14 |
| SBS 300 | 1109 | 719 | 534 | 430 | 247 | 174 | 136 | 113 | 97 | 84 | 75 | 62 | 35 |
| SBS 390 | 1185 | 797 | 608 | 495 | 290 | 208 | 163 | 134 | 114 | 99 | 88 | 72 | 39 |
| SBS J13 | 52 | 31 | 23 | 18 | 10 | 7.1 | 5.5 | 4.5 | 3.8 | 3.3 | 2.9 | 2.4 | 1.3 |
| SBS J16 | 65 | 40 | 29 | 23 | 13 | 9.2 | 7.2 | 5.9 | 5.0 | 4.3 | 3.8 | 3.1 | 1.6 |
| SBS J30 | 119 | 72 | 52 | 41 | 23 | 16 | 12 | 10 | 8.5 | 7.4 | 6.5 | 5.3 | 2.8 |
| SBS J40 | 166 | 103 | 76 | 60 | 34 | 24 | 18 | 15 | 13 | 11 | 10 | 7.9 | 4.2 |
| SBS J70 | 281 | 173 | 126 | 100 | 55 | 38 | 29 | 24 | 20 | 18 | 15 | 13 | 6.5 |
| SBS B8(F) | 132 | 77 | 56 | 44 | 25 | 18 | 14 | 11 | 10 | 8.5 | 7.5 | 6.2 | 3.3 |
| SBS B10(F) | 150 | 91 | 66 | 52 | 30 | 21 | 16 | 14 | 12 | 10 | 9.2 | 7.7 | 4.3 |
| SBS B14(F) | 229 | 145 | 108 | 87 | 50 | 36 | 28 | 23 | 20 | 17 | 16 | 13 | 6.9 |
| SBS C11(F) | 318 | 205 | 153 | 123 | 71 | 51 | 40 | 33 | 28 | 25 | 22 | 18 | 10 |
| SBS 100(F) | 358 | 235 | 177 | 143 | 82 | 59 | 46 | 37 | 32 | 28 | 25 | 20 | 11 |
| SBS 112F | 359 | 239 | 183 | 149 | 88 | 64 | 50 | 41 | 35 | 31 | 27 | 22 | 12 |
| SBS 145F | 483 | 309 | 231 | 186 | 108 | 77 | 61 | 51 | 44 | 39 | 35 | 29 | 15 |
| SBS 165F | 569 | 374 | 283 | 234 | 136 | 97 | 76 | 62 | 54 | 47 | 42 | 34 | 18 |
| SBS 170F | 535 | 372 | 289 | 237 | 139 | 100 | 78 | 64 | 54 | 48 | 42 | 35 | 19 |
| SBS 190F | 606 | 418 | 323 | 264 | 157 | 113 | 88 | 72 | 62 | 54 | 48 | 39 | 21 |

Constant Power Discharge Performance Data continued

Discharge Power (Watts per Cell) to 1.80Vpc at 77°F (25°C)

| Battery Type | Standby Time (Minutes) | | | Standby Time (Hours) | | | | | | | | | |
|--------------|------------------------|-----|-----|----------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| | 15 | 30 | 45 | 1 | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 10 | 20 |
| SBS 8 | 34 | 20 | 14 | 11 | 6.2 | 4.3 | 3.3 | 2.7 | 2.3 | 2.0 | 1.8 | 1.5 | 0.8 |
| SBS 15 | 61 | 37 | 27 | 21 | 12 | 8.4 | 6.5 | 5.3 | 4.5 | 3.9 | 3.5 | 2.8 | 1.5 |
| SBS 30 | 113 | 68 | 50 | 39 | 22 | 15 | 12 | 10 | 8.3 | 7.2 | 6.4 | 5.3 | 2.9 |
| SBS 40 | 153 | 95 | 70 | 56 | 31 | 22 | 17 | 14 | 12 | 10 | 9.1 | 7.5 | 4.1 |
| SBS 60 | 198 | 124 | 92 | 74 | 42 | 30 | 23 | 19 | 16 | 14 | 12 | 10 | 5.5 |
| SBS J13 | 50 | 31 | 23 | 18 | 10 | 7.1 | 5.5 | 4.5 | 3.8 | 3.3 | 2.9 | 2.4 | 1.2 |
| SBS J16 | 63 | 39 | 29 | 23 | 13 | 9.1 | 7.0 | 5.8 | 4.9 | 4.3 | 3.8 | 3.1 | 1.6 |
| SBS J30 | 115 | 71 | 52 | 41 | 23 | 16 | 12 | 10 | 8.4 | 7.3 | 6.5 | 5.3 | 2.8 |
| SBS J40 | 161 | 101 | 74 | 59 | 33 | 23 | 18 | 15 | 13 | 11 | 10 | 7.8 | 4.1 |
| SBS J70 | 269 | 168 | 123 | 98 | 55 | 38 | 29 | 24 | 20 | 17 | 15 | 12 | 6.5 |
| SBS 110 | 371 | 247 | 188 | 153 | 90 | 65 | 51 | 42 | 36 | 31 | 28 | 23 | 12 |
| SBS 130 | 439 | 286 | 216 | 175 | 103 | 74 | 58 | 48 | 41 | 36 | 32 | 26 | 14 |
| SBS 300 | 1048 | 688 | 510 | 411 | 238 | 168 | 133 | 110 | 95 | 83 | 74 | 62 | 35 |
| SBS 390 | 1144 | 779 | 597 | 486 | 286 | 206 | 161 | 133 | 113 | 98 | 87 | 71 | 38 |
| SBS B8(F) | 131 | 76 | 55 | 44 | 25 | 18 | 14 | 11 | 10 | 8.5 | 7.5 | 6.1 | 3.3 |
| SBS B10(F) | 147 | 90 | 65 | 52 | 29 | 21 | 16 | 14 | 12 | 10 | 9.2 | 7.7 | 4.3 |
| SBS B14(F) | 219 | 140 | 105 | 85 | 49 | 35 | 28 | 23 | 20 | 17 | 15 | 13 | 6.9 |
| SBS C11(F) | 305 | 199 | 150 | 121 | 71 | 50 | 40 | 33 | 28 | 25 | 22 | 18 | 10 |
| SBS 100(F) | 337 | 224 | 171 | 138 | 81 | 58 | 45 | 37 | 31 | 27 | 24 | 20 | 11 |
| SBS 112F | 338 | 229 | 177 | 145 | 87 | 63 | 49 | 41 | 35 | 30 | 27 | 22 | 11 |
| SBS 145F | 457 | 300 | 225 | 182 | 107 | 76 | 60 | 50 | 44 | 38 | 34 | 28 | 15 |
| SBS 165F | 537 | 361 | 275 | 228 | 133 | 95 | 74 | 61 | 53 | 46 | 41 | 34 | 18 |
| SBS 170F | 493 | 355 | 279 | 230 | 137 | 98 | 77 | 63 | 54 | 47 | 42 | 34 | 19 |
| SBS 190F | 566 | 399 | 311 | 257 | 154 | 111 | 87 | 72 | 61 | 53 | 47 | 39 | 21 |

Discharge Power (Watts per Cell) to 1.85Vpc at 77°F (25°C)

| Battery Type | Standby Time (Minutes) | | | Standby Time (Hours) | | | | | | | | | |
|--------------|------------------------|-----|-----|----------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| | 15 | 30 | 45 | 1 | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 10 | 20 |
| SBS 8 | 32 | 19 | 14 | 11 | 6.0 | 4.2 | 3.3 | 2.7 | 2.3 | 2.0 | 1.8 | 1.5 | 0.8 |
| SBS 15 | 59 | 36 | 27 | 21 | 12 | 8.2 | 6.4 | 5.2 | 4.4 | 3.9 | 3.4 | 2.8 | 1.5 |
| SBS 30 | 110 | 67 | 49 | 39 | 21 | 15 | 12 | 10 | 8.1 | 7.1 | 6.3 | 5.2 | 2.8 |
| SBS 40 | 148 | 93 | 69 | 55 | 31 | 21 | 17 | 14 | 12 | 10 | 8.9 | 7.3 | 4.0 |
| SBS 60 | 188 | 120 | 89 | 71 | 41 | 29 | 23 | 19 | 16 | 14 | 12 | 10 | 5.3 |
| SBS J13 | 48 | 30 | 22 | 17 | 10 | 6.9 | 5.4 | 4.4 | 3.7 | 3.2 | 2.9 | 2.3 | 1.2 |
| SBS J16 | 60 | 38 | 28 | 22 | 12 | 8.7 | 6.8 | 5.6 | 4.7 | 4.1 | 3.6 | 3.0 | 1.6 |
| SBS J30 | 110 | 69 | 50 | 40 | 22 | 15 | 12 | 10 | 8.2 | 7.1 | 6.3 | 5.1 | 2.7 |
| SBS J40 | 153 | 98 | 72 | 57 | 32 | 23 | 18 | 14 | 12 | 11 | 9.4 | 7.6 | 4.0 |
| SBS J70 | 253 | 161 | 119 | 95 | 53 | 37 | 29 | 23 | 20 | 17 | 15 | 12 | 6.3 |
| SBS 110 | 353 | 239 | 183 | 149 | 88 | 63 | 50 | 41 | 35 | 31 | 27 | 23 | 12 |
| SBS 130 | 418 | 275 | 208 | 170 | 100 | 73 | 57 | 47 | 40 | 35 | 31 | 26 | 14 |
| SBS 300 | 976 | 625 | 468 | 379 | 221 | 159 | 126 | 105 | 90 | 80 | 72 | 60 | 34 |
| SBS 390 | 1085 | 749 | 575 | 472 | 279 | 200 | 157 | 130 | 112 | 96 | 85 | 70 | 38 |
| SBS B8(F) | 129 | 76 | 54 | 43 | 24 | 17 | 14 | 11 | 10 | 8.4 | 7.4 | 6.1 | 3.2 |
| SBS B10(F) | 142 | 89 | 64 | 51 | 29 | 20 | 16 | 13 | 11 | 10 | 9.0 | 7.5 | 4.2 |
| SBS B14(F) | 205 | 133 | 101 | 82 | 48 | 35 | 27 | 23 | 20 | 17 | 15 | 13 | 6.9 |
| SBS C11(F) | 288 | 190 | 144 | 117 | 69 | 50 | 39 | 33 | 28 | 25 | 22 | 18 | 10 |
| SBS 100(F) | 311 | 210 | 161 | 131 | 78 | 56 | 44 | 36 | 31 | 27 | 24 | 20 | 11 |
| SBS 112F | 312 | 215 | 167 | 138 | 84 | 61 | 48 | 40 | 34 | 29 | 26 | 21 | 11 |
| SBS 145F | 425 | 283 | 216 | 176 | 103 | 74 | 59 | 49 | 43 | 37 | 33 | 27 | 14 |
| SBS 165F | 501 | 344 | 265 | 222 | 130 | 93 | 73 | 60 | 52 | 46 | 41 | 33 | 18 |
| SBS 170F | 469 | 337 | 268 | 221 | 132 | 95 | 74 | 61 | 52 | 46 | 40 | 33 | 18 |
| SBS 190F | 522 | 375 | 296 | 246 | 149 | 108 | 85 | 70 | 60 | 52 | 46 | 38 | 21 |



Visit us at www.enersys.com



Power/Full Solutions

EnerSys World Headquarters
2366 Bernville Road
Reading, PA 19605, USA
Tel: +1-610-208-1991 /
+1-800-538-3627

EnerSys EMEA
EH Europe GmbH
Baarerstrasse 18
6300 Zug, Switzerland

EnerSys Asia
152 Beach Road
Gateway East Building #11-03
Singapore 189721
Tel: +65 6508 1780