

Output Adapters

For PowerBay+[™] BDFB Advanced Modular Distribution Bay

an EnerSys® company



- Single- and multi-pole adapters for AM and GJ breaker panels
- Wide variety of compatible lug compatibility

Alpha[®] offers a variety of breaker panel output lug adapters for the PowerBay+[™] BDFB distribution bay.

Single-pole and multi-pole output lug adapters are available in a variety of sizes and angles to ease cable routing and allow maximum space. Alpha stocks a wide range of lugs, terminals and taps for almost any telecom power need.

Output Adapter Specifications

AM Breaker Panel Output Adapter Brackets					
Part Number	Description	Pole Count	Angle	2-Hole Lug Connection	Compatibility
C590-2267-10	Double-pole straight bracket, AM breaker panel	2	Straight	3/8" threaded studs, 1" CTC	800A AM breaker panel, 1200A AM breaker panel
C590-2483-10	Double-pole 45 $^\circ$ bracket, AM breaker panel	2	45°	3/8" threaded studs, 1" CTC	800A AM breaker panel, 1200A AM breaker panel
C590-2268-10	Triple-pole straight bracket, AM breaker panel	3	Straight	3/8" threaded studs, 1" CTC	800A AM breaker panel, 1200A AM breaker panel
C590-2484-10	Triple-pole 45° bracket, AM breaker panel	3	45°	3/8" threaded studs, 1" CTC	800A AM breaker panel, 1200A AM breaker panel
GJ Breaker Pane	el Output Adapter Brackets				
_					
GJ Breaker Pane Part Number	el Output Adapter Brackets Description	Pole Count	Angle	2-Hole Lug Connection	Compatibility
	<u> </u>	Pole Count	Angle 90°	2-Hole Lug Connection 3/8" through holes, 1" (TC	Compatibility 1200A GJ breaker panel
Part Number	Description	Pole Count 1 1			
Part Number C590-1890-10	Description Single-pole 90° bracket, GJ breaker panel	Pole Count 1 2	90°	3/8" through holes, 1" CTC	1200A GJ breaker panel
Part Number (590-1890-10 (590-1891-10	Description Single-pole 90° bracket, GJ breaker panel Single-pole 45° bracket, GJ breaker panel	1	90° 45°	3/8" through holes, 1" CTC 3/8" through holes, 1" CTC	1200A GJ breaker panel 1200A GJ breaker panel
Part Number (590-1890-10 (590-1891-10 (590-2411-10	Description Single-pole 90° bracket, GJ breaker panel Single-pole 45° bracket, GJ breaker panel Double-pole 90° bracket, GJ breaker panel	1	90° 45° 90°	3/8" through holes, 1" CTC 3/8" through holes, 1" CTC 3/8" through holes, 1" CTC	1200A GJ breaker panel 1200A GJ breaker panel 1200A GJ breaker panel

BDFB Internal Return Bus Output Adapter Brackets Compatibility Part Number Description Pole Count Angle 2-Hole Lug Connection C590-2407-10 Double-pole straight bracket, internal return bus, AM/GJ breaker panel 2 Straight 3/8" threaded inserts, 1" CTC PowerBay+ BDFB distribution bays with internal return bus C590-2408-10 Triple-pole straight bracket, internal return bus, AM/GJ breaker panel 3 Straight 3/8" threaded inserts, 1" CTC PowerBay+ BDFB distribution bays with internal return bus



Alpha Technologies Services, Inc. USA: 3767 Alpha Way, Bellingham, WA 98226 Canada: 7700 Riverfront Gate, Burnaby, BC V5J 5M4 Toll Free North America: +1 800 322 5742 Outside US: +1 360 647 2360 Technical Support: +1 800 863 3364 For more information visit www.alpha.com

© 2021 Alpha Technologies Services, Inc. All Rights Reserved. Trademarks and logos are the property of Alpha Technologies Services, Inc., EnerSys and its affiliates unless otherwise noted. Subject to revisions without prior notice. E. & O.E.

an EnerSys® company