



## **SIMPLY POWERFUL, ALWAYS DEPENDABLE**

Maximize value and efficiency while reducing ownership costs with Elitra™ iON batteries that keep your operations running smoothly, allowing you to focus on more important priorities.

Designed for cost-effectiveness, essential performance, and safety, Elitra™ iON batteries deliver reliable, maintenance-free power to demanding applications.



### **PEAK PRODUCTIVITY**

Extended equipment run times with higher sustained voltages and fast recharge rates.



### **DEPENDABLE DESIGN**

Unique primary and secondary Battery Management System ensuring your seamless operations with essential safety.



# POWER YOUR OPERATION WITH SIMPLICITY AND RELIABILITY

| Model       | Voltage | Nominal Voltage | Total Ah Capacity | Module | Configured | Modular Design |
|-------------|---------|-----------------|-------------------|--------|------------|----------------|
|             | V       | V               | Ah                | kWh    | kWh        |                |
| 24-L1-2.7L  | 24      | 25.6            | 104               | 2.66   | 2.7        | 1              |
| 24-L1-5.3L  | 24      | 25.6            | 208               | 2.66   | 5.3        | 2              |
| 24-L1-8.0L  | 24      | 25.6            | 312               | 2.66   | 8.0        | 3              |
| 24-L1-10.6L | 24      | 25.6            | 416               | 2.66   | 10.6       | 4              |
| 24-L1-13.3L | 24      | 25.6            | 520               | 2.66   | 13.3       | 5              |
| 24-L1-16.0L | 24      | 25.6            | 624               | 2.66   | 16.0       | 6              |
| 24-L1-18.6L | 24      | 25.6            | 728               | 2.66   | 18.6       | 7              |
| 24-L1-21.3L | 24      | 25.6            | 832               | 2.66   | 21.3       | 8              |
| 24-L1-24.0L | 24      | 25.6            | 936               | 2.66   | 24.0       | 9              |
| 24-L1-26.6L | 24      | 25.6            | 1040              | 2.66   | 26.6       | 10             |
| 36-L1-4.0L  | 36      | 38.4            | 104               | 3.99   | 4.0        | 1              |
| 36-L1-8.0L  | 36      | 38.4            | 208               | 3.99   | 8.0        | 2              |
| 36-L1-12.0L | 36      | 38.4            | 312               | 3.99   | 12.0       | 3              |
| 36-L1-16.0L | 36      | 38.4            | 416               | 3.99   | 16.0       | 4              |
| 36-L1-20.0L | 36      | 38.4            | 520               | 3.99   | 20.0       | 5              |
| 36-L1-24.0L | 36      | 38.4            | 624               | 3.99   | 24.0       | 6              |
| 36-L1-28.0L | 36      | 38.4            | 728               | 3.99   | 28.0       | 7              |
| 36-L1-31.9L | 36      | 38.4            | 832               | 3.99   | 31.9       | 8              |
| 36-L1-35.9L | 36      | 38.4            | 936               | 3.99   | 35.9       | 9              |
| 36-L1-39.9L | 36      | 38.4            | 1040              | 3.99   | 39.9       | 10             |
| 48-L1-5.3L  | 48      | 51.2            | 104               | 5.32   | 5.3        | 1              |
| 48-L1-10.6L | 48      | 51.2            | 208               | 5.32   | 10.6       | 2              |
| 48-L1-16.0L | 48      | 51.2            | 312               | 5.32   | 16.0       | 3              |
| 48-L1-21.3L | 48      | 51.2            | 416               | 5.32   | 21.3       | 4              |
| 48-L1-26.6L | 48      | 51.2            | 520               | 5.32   | 26.6       | 5              |
| 48-L1-31.9L | 48      | 51.2            | 624               | 5.32   | 31.9       | 6              |
| 48-L1-37.3L | 48      | 51.2            | 728               | 5.32   | 37.3       | 7              |
| 48-L1-42.6L | 48      | 51.2            | 832               | 5.32   | 42.6       | 8              |
| 48-L1-47.9L | 48      | 51.2            | 936               | 5.32   | 47.9       | 9              |
| 48-L1-53.2L | 48      | 51.2            | 1040              | 5.32   | 53.2       | 10             |
| 72-L1-8.0L  | 72      | 76.8            | 104               | 3.99   | 8.0        | *2             |
| 72-L1-16.0L | 72      | 76.8            | 208               | 3.99   | 16.0       | *4             |
| 72-L1-24.0L | 72      | 76.8            | 312               | 3.99   | 24.0       | *6             |
| 72-L1-31.9L | 72      | 76.8            | 416               | 3.99   | 31.9       | *8             |
| 72-L1-39.9L | 72      | 76.8            | 520               | 3.99   | 39.9       | *10            |
| 72-L1-47.9L | 72      | 76.8            | 624               | 3.99   | 47.9       | *12            |
| 72-L1-55.9L | 72      | 76.8            | 728               | 3.99   | 55.9       | *14            |
| 72-L1-63.9L | 72      | 76.8            | 832               | 3.99   | 63.9       | *16            |
| 72-L1-71.9L | 72      | 76.8            | 936               | 3.99   | 71.9       | *18            |
| 72-L1-79.9L | 72      | 76.8            | 1040              | 3.99   | 79.9       | *20            |
| 80-L1-8.7L  | 80      | 83.2            | 104               | 4.33   | 8.7        | **2            |
| 80-L1-17.3L | 80      | 83.2            | 208               | 4.33   | 17.3       | **4            |
| 80-L1-26.0L | 80      | 83.2            | 312               | 4.33   | 26.0       | **6            |
| 80-L1-34.6L | 80      | 83.2            | 416               | 4.33   | 34.6       | **8            |
| 80-L1-43.3L | 80      | 83.2            | 520               | 4.33   | 43.3       | **10           |
| 80-L1-51.9L | 80      | 83.2            | 624               | 4.33   | 51.9       | **12           |
| 80-L1-60.6L | 80      | 83.2            | 728               | 4.33   | 60.6       | **14           |
| 80-L1-69.2L | 80      | 83.2            | 832               | 4.33   | 69.2       | **16           |
| 80-L1-77.9L | 80      | 83.2            | 936               | 4.33   | 77.9       | **18           |
| 80-L1-86.5L | 80      | 83.2            | 1040              | 4.33   | 86.5       | **20           |

\* 2 x 36V Power Modules are connected in series to 72V

\*\* 2 x 40V Power Modules are connected in series to 80V

[www.enersys.com](http://www.enersys.com)

© 2025 EnerSys. All rights reserved. Trademarks and logos are the property of EnerSys and its. Subject to revisions without prior notice. E.&O.E.  
APAC-SR-EN-TD-ELI-LFP-ION-0825

